MᴄGɪɴɴ Iɴᴛᴇʟʟᴇᴄᴛᴜᴀʟ Pʀᴏᴘᴇʀᴛʏ Lᴀᴡ Gʀᴏᴜᴘ, PLLC
A Pʀᴏꜰᴇssɪᴏɴᴀʟ Lɪᴍɪᴛᴇᴅ Lɪᴀʙɪʟɪᴛʏ Cᴏᴍᴘᴀɴʏ
Pᴀᴛᴇɴᴛs, Tʀᴀᴅᴇᴍᴀʀᴋs, Cᴏᴘʏʀɪɢʜᴛs, ᴀɴᴅ Iɴᴛᴇʟʟᴇᴄᴛᴜᴀʟ Pʀᴏᴘᴇʀᴛʏ Lᴀᴡ
8321 Oʟᴅ Cᴏᴜʀᴛʜᴏᴜsᴇ Rᴏᴀᴅ, Sᴜɪᴛᴇ 200
Vɪᴇɴɴᴀ, Vɪʀɢɪɴɪᴀ 22182-3817
Tᴇʟᴇᴘʜᴏɴᴇ (703) 761-4100
Fᴀᴄsɪᴍɪʟᴇ (703) 761-2375; (703) 761-2376

APPLICATION
FOR
UNITED STATES
LETTERS PATENT

APPLICANT: Yoichi KATAYAMA

FOR: IMAGE DECODING APPARATUS AND
IMAGE DECODING METHOD

DOCKET NO.:   04USFP1024-M.K.

DESCRIPTION

IMAGE DECODING APPARATUS AND IMAGE DECODING METHOD

5 **Technical Field**

The present invention relates to an image decoding apparatus and an image decoding method.

Background Art

10   In recent years, with the wide use of information equipments such as a personal computer, the population of a digital camera and a color printer, and the explosive increase of users of the Internet, the technique of a digital image has spread

15 over daily life. The coding compression techniques such as JPEG (Joint Photographic Expert Group) and MPEG (Motion Picture Expert Group) are standardized for a static image and a video image, respectively.

On the other hand, the replaying technique of

20 a recording media such as CD-ROM has been improved, and the convenience of the delivery and replaying of image data through transmission media such as a network or a broadcasting has been improved. As for the JPEG, JPEG 2000 as an evolution edition is

25 released, and also goals in middle and long ranges of the MPEG are settled. In this way, it could be considered that the image processing technique for the

1

information equipment could be further improved in future.

A conventional decoding method of the above JPEG 2000 is disclosed in Japanese Laid Open Patent Application (JP-P2002-325257A). Fig. 1 shows the structure of an image decoding apparatus 10 in this conventional example. This conventional image decoding apparatus 10 may be realized by a CPU, a memory, and other LSIs in hardware. Also, this conventional image decoding apparatus 10 may be realized by a program having an image decoding function in software. Fig. 1 is a schematic functional block diagram showing the image decoding apparatus realized through cooperation of them. Therefore, a person in the art could understand that the functional block can be realized by only the hardware, only the software or those combinations.

The above-mentioned image decoding apparatus 10 is composed of a decoding section 12 and a simplification section 30 mainly. The decoding unit 12 contains a stream analyzing section 14, an arithmetic decoding section 16, a bit modeling decoding section 18, an inverse quantization section 20 and an inverse wavelet conversion section 24.

The stream analyzing section 14 receives and analyzes a compressed data (coded image data) CI, and the arithmetic decoding section 16 carries out an

2

arithmetic decoding process to the coded image data CI based on the result of the analysis. The bit modeling decoding section 18 decodes the data obtained as the result of the arithmetic decoding process in the form

5 of a bit plane for every color component, and the inverse quantization section 20 carries out an inverse quantization process to the decoding result by the bit modeling decoding section 18. The inverse wavelet conversion section 24 carries out an inverse wavelet

10 conversion process to an image WIn of the n-th layer obtained as the result of the inverse quantization process. The inverse wavelet conversion section 24 uses a frame buffer (not shown) as a work area. Finally, a decoded image DI is outputted from the

15 frame buffer.

On the other hand, the simplification section 30 contains a converting section 32, a time table 34 and a replay stop detecting section 36. The converting section 32 monitors the progress situation

20 of the decoding process by the inverse wavelet conversion section 24 and switches the decoding process to a simplifying process compulsorily, when the time exceeds a predetermined time limit. The time table 34 stores a time limit to be referred to by the

25 converting section 32, and the replay stop detecting section 36 detects a fact that the user instructs the replay of the image to be stopped.

A frame which is being decoded and replayed when the user instructs suspension or end of the decoding or replaying operation is actually released from the time limit of the decoding process.

5   Therefore, when the instruction of the suspension or end of the replaying operation is detected by the replay stop detecting section 36, the simplifying process to the frame by the converting section 32 is avoided and the replaying operation is fully carried

10   out, like the usual manner. However, there is a case that the simplifying process by the converting section 32 has already begun. In such a case, the subsequent decoding process is carried out as usually as possible.

15   The converting section 32 refers to a clock signal CLK to measure the elapsed time. The clock signal CLK is frequency-divided in the converting section 32 according to necessity, and is counted by a counter (not shown) to measure a predetermined time.

20   Also, the converting section 32 may refer to an externally provided time clock section such as a PIT (programmable interrupt timer) instead of the clock signal CLK. Also, in this example, the converting section 32 monitors the decoding process of the

25   inverse wavelet conversion section 24. However, it is not always necessary for the converting section 32 to monitor the decoding process of the inverse wavelet

4

conversion section 24. The elapsed time of either of the decoding processes from the stream analyzing section 14 to the inverse wavelet conversion section 24 may be monitored.

5   As seen the above description, in the conventional image decoding apparatus, it is necessary to provide the converting section 32 to compulsively stop the decoding process for all or each of the decoding sections. Therefore, it is difficult to

10   control the process time optimization of the whole system. Also, the converting section 32 compulsively stops the subsequent processes so that the control cannot be carried out accurately. As a result, it is difficult to suppress the degradation of image

15   quality.

Disclosure of Invention

Therefore, an object of the present invention to provide an image decoding apparatus and an image

20   decoding method, in which it is possible to carry out the control of process time optimization of the whole system so that the degradation of image quality can be suppressed.

In an aspect of the present invention, an

25   image decoding apparatus includes an analyzing section and an image decoding section. The analyzing section determines a process quantity of a coded image data to

each of a plurality of image decoding processes within
a unit process time based on a parameter for the coded
image data, prior to the plurality of image decoding
processes. The image decoding section carries out
5   each of the plurality of image decoding processes to
the coded image data for the determined process
quantity such that a decoded image data is generated
from the coded image data.

Here, the parameter may an internal parameter
10 of the coded image data, or maybe an external
parameter for the coded image data. Instead, the
parameter contains is an external parameter for the
coded image data, and an external parameter for the
coded image data.

15   Also, when the coded image data includes a
plurality of code blocks, the analyzing section may
determine the process quantity to each of the
plurality of image decoding processes by determining a
code block process quantity for each of the plurality
20 of code blocks based on the unit process time.

Also, when the coded image data is a part of
a coded image data stream, and a stream process time
of the coded image data stream is previously
determined, the unit process time may be determined
25 based on a number of the coded image data in the coded
image data stream and the stream process time. In
this case, the plurality of decoding processes may

contain an arithmetic decoding process, a bit modeling

decoding process, an inverse quantization process and

an inverse wavelet conversion process. The image

decoding section may carry out a set of the arithmetic

5 decoding process and the bit modeling decoding

process, the inverse quantization process, and the

inverse wavelet conversion process in a pipeline. In

this case, the image decoding section may include an

arithmetic decoding section which carries out the

10 arithmetic decoding process to the coded image data

for the determined process quantity; a bit modeling

decoding section which carries out the bit modeling

decoding process to a result of the arithmetic

decoding process by the arithmetic decoding section in

15 a form of bit planes every color component for the

determined process quantity; an inverse quantization

section which carries out the inverse quantization

process to a result of the bit modeling decoding

process by the bit modeling decoding section for the

20 determined process quantity; and an inverse wavelet

conversion process section which carries out the

inverse wavelet conversion process to a result of the

inverse quantization process by the inverse

quantization section for the determined process

25 quantity.

   Also, when the coded image data is encoded

into a plurality of layers, the analyzing section may

determine a number of layers to be decoded based on
the process quantity of the coded image data in the
inverse quantization process and the process quantity
of the coded image data in the inverse wavelet

5   conversion process. The image decoding section may
carry out each of the plurality of decoding processes
to the coded image data for the determined number of
layers to be decoded. In this case, the analyzing
section may discard a part of the coded image data

10 other than a part of the coded image data associating
with the determined number of layers to be decoded.
In this case, the plurality of decoding processes may
contain an arithmetic decoding process, a bit modeling
decoding process, an inverse quantization process and

15 an inverse wavelet conversion process, and each of the
plurality of layers of the coded image data may
contain a plurality of code blocks. The parameter
desirably contains a weight coefficient allocated to
each of the plurality of code blocks. The analyzing

20 section may determine a number of coding paths in the
arithmetic decoding process and the bit modeling
decoding process to each of the plurality of code
blocks from the weight coefficients and the unit
process time, and may determine a number of bit planes

25 from the determined coding paths. The image decoding
section may carry out the inverse quantization process
and the inverse wavelet conversion process to the

coded image data for the determined number of bit planes.

In another aspect of the present invention, an image decoding method of decoding a decoded image data from a coded image data through a plurality of decoding processes, is achieved by determining a process quantity of the coded image data in each of the plurality of image decoding processes within a unit process time based on a parameter of the coded image data; and by carrying out the plurality of image decoding processes to the coded image data for the determined process quantities.

Here, the parameter may an internal parameter of the coded image data, or maybe an external parameter for the coded image data. Instead, the parameter contains is an external parameter for the coded image data, and an external parameter for the coded image data.

Also, when the coded image data contains a plurality of code blocks, the determining a process quantity may be achieved by determining the process quantity by determining a code block process quantity allocated to each of the plurality of code blocks based on the unit process time. In this case, when the coded image data is a part of a coded image data stream, and a stream process time of the coded image data stream is predetermined, the image decoding

method further may be achieved by determining the unit

process time based on a number of the coded image data

in the coded image data stream and the stream process

time. Also, the plurality of decoding processes may

5   contain an arithmetic decoding process, a bit modeling

decoding process, an inverse quantization process and

an inverse wavelet conversion process. At this time,

the carrying out the plurality of image decoding

processes may be achieved by carrying out a set of the

10   arithmetic decoding process and the bit modeling

decoding process, the inverse quantization process,

and the inverse wavelet conversion process in a

pipeline. In this case, the carrying out the

plurality of image decoding processes may include

15   carrying out the arithmetic decoding process to the

coded image data for the determined process quantity;

carrying out the bit modeling decoding process to a

result of the arithmetic decoding process for the

determined process quantity; carrying out the inverse

20   quantization process to a result of the bit modeling

decoding process for the determined process quantity;

and carrying out the inverse wavelet conversion

process to a result of the inverse quantization

process for the determined process quantity.

25   Also, when the coded image data is encoded in

a plurality of layers, the determining a process

quantity may be achieved by determining a number of

10

layers to be decoded based on the process quantities of the coded image data in the inverse quantization process and the process quantity of the coded image data in the inverse wavelet conversion process. Also, the carrying out the plurality of image decoding processes may be achieved by carrying out each of the plurality of decoding processes to the coded image data for the determined number of layers to be decoded.

The image decoding method may further include discarding a part of the coded image data other than a part of the coded image data corresponding to the determined number of layers to be decoded.

Also, the plurality of decoding processes may contain an arithmetic decoding process, a bit modeling decoding process, an inverse quantization process and an inverse wavelet conversion process. Each of the plurality of layers of the coded image data may contain a plurality of code blocks. The parameter contains a weight coefficient allocated to each of the plurality of code blocks. The determining a process quantity may include determining a number of coding paths in the arithmetic decoding process and the bit modeling decoding process to each of the plurality of code blocks from the weight coefficients and the unit process time; and determining a number of bit planes from the determined coding paths. The carrying out

11

the plurality of image decoding processes may be achieved by carrying out the inverse quantization process and the inverse wavelet conversion process to the coded image data for the determined number of bit

5   planes.

In another aspect of the present invention, a computer-readable recording medium on which a software is recorded to realize the above image decoding method.

10

Brief Description of Drawings

Fig. 1 is a block diagram showing the structure of a conventional image decoding apparatus;

Fig. 2 is a block diagram showing the

15 structure of an image decoding apparatus according to a first embodiment of the present invention;

Fig. 3 is a diagram showing an example of an image to which JPEG coding is applied;

Fig. 4 is a block diagram showing the

20 structure of a modification example of the image decoding apparatus according to the first embodiment of the present invention;

Fig. 5 is a diagram showing a pipeline processing of the image decoding apparatus according

25 to the first embodiment of the present invention;

Fig. 6 is a flow chart showing an operation of the image decoding apparatus according to the first

embodiment of the present invention;

Figs. 7A and 7B are diagrams showing a method of allocating a unit process time in the image decoding apparatus according to the first embodiment of the present invention;

Fig. 8 is a diagram showing a weight coefficient allocated to each code block of the coded image data;

Fig. 9 is a diagram showing an original data process quantity of each code block and allocated data process quantity to an inverse quantization process and an inverse wavelet conversion process;

Figs. 10A and 10B are a flow chart of the inverse quantization process to determine the number of layers to be processed and a diagram showing an example of a result of the inverse quantization process;

Figs. 11A and 11B are a flow chart of the inverse wavelet conversion process to determine the number of layers to be processed and a diagram showing an example of a result of the inverse wavelet conversion process;

Fig. 12 is a flow chart showing an arithmetic decoding process and a bit modeling decoding process;

Figs. 13, 14 and 15 are flow charts showing the details of the decoding process shown in Fig. 12; and

Fig. 16 is a diagram showing decomposition of each code block into coding paths.

Best Mode for Carrying Out the Invention

5   Hereinafter, an image decoding apparatus of the present invention will be described in detail with reference to the attached drawings.

For easy understanding of the present invention, a coding procedure will be first described.
10   In JPEG 2000, a Daubechies filter is used as a wavelet conversion filter and its essence lies in the point that a high-pass filter and a low-pass filter are applied to an image in horizontal (x) and vertical (y) directions at the same time. Also, this filter has a
15   function to reduce the number of pixels to 1/2 in both directions of x and y. Therefore, if the decoded image DI is an original image in Fig. 1, an image WI1 of the first layer is generated to have code blocks (sub bands) of 1LL, 1LH, 1HL, and 1HH, when the
20   wavelet conversion process is carried out to this image once, as shown in Fig. 3. The 1LL code block shows a low frequency component of the image in the directions of x and y, and each of the HL code block and the LH code block shows a low frequency component
25   of the image in one of the directions of x and y and a high frequency component in the other direction. The HH code block shows a high frequency component of the

14

image in the directions of x and y. In this way, the low frequency component of the original image appears on the upper left portion (1LL portion) in the converted image.

5   When the second wavelet conversion process is carried out, an image WI2 of the second layer is generated. The second wavelet conversion process is carried out only to the LL code block of the code blocks of a layer obtained through the immediately 10 previous wavelet conversion process. Therefore, the 1LL code block of the image WI1 of the first layer is decomposed into four code blocks 2LL, 2HL, 2LH, 2HH in the image WI2 of the second layer. When the third wavelet conversion process is carried out, an image 15 WI3 of the third layer is generated. The third wavelet conversion process is carried out only to the 2LL code block out of the image of the second layer. Therefore, the 2LL code block of the image WI2 of the second layer is decomposed into four code blocks 3LL, 20 3HL, 3LH, 3HH in the image WI3 of the third layer. The 3LL code block shows the lowest frequency component. Oppositely saying, the most basic nature of the original image can be replayed if this 3LL code block can be obtained, and it is possible to say that 25 it is an important block. In the coding process, a coded image data CI is finally obtained through the quantization, and the other process after this.

Next, the image decoding apparatus according to the first embodiment of the present invention will be described. Fig. 2 is a block diagram showing the structure of the image decoding apparatus according to the first embodiment of the present invention. Referring to Fig. 2, the image decoding apparatus 100 according to the first embodiment of the present invention is composed of a compressed data analyzing section 102 and an image decoding section 112. The compressed data analyzing section 102 has a code buffer 103 which receives a compressed data (coded image data) CI, a data quantity determining section 107 and an address generating circuit 104 which receives the output 105 of the data quantity determining section 107. In the compressed data analyzing section 102, the code buffer 103 receives the compressed data (coded image data) CI, and stores therein. The compressed data may be a stream of compressed data (coded image data). The stored data is outputted to the data quantity determining section 107 in accordance with an address from the address generating circuit 104.

The data quantity determining section 107 calculates a process quantity such as a data quantity or process time in each of various processes. The data quantity determining section 107 is supplied with a control parameter 101 which contains a unit process

time Ti of one frame image (=t_{total}/the total number of

frames), the number of code blocks (SB), a code block

size (CBS), the number of bit planes BP(CB_i) (CB_i shows

a code block number (coordinate)), the number of

5   quantization steps qs(SB_i) (SB_i shows a sub band number

(coordinate)), and a weighting quantity W(CB_i) of the

code block CB_i. The data quantity determining section

107 analyzes the compressed data CI, determines the

process quantity 105 every code block by using the

10   control parameter 101 and outputs it to the address

generating circuit 104. The address generating

circuit 104 generates an address based on the process

quantities 105 and output it to the code buffer 103.

Thus, the whole or part of the coded image is

15   outputted as a data stream 108 from the code buffer

103 to the image decoding section 112 together with

the process quantities. The image decoding section

112 decodes the data stream 108 outputted from the

compressed data analyzing section 102 based on the

20   determined process quantities 105 from the compressed

data analysis section 102 and replays an original

image (decoded Image) DI. In this case, the process

quantities 105 may be outputted directly to the image

decoding section 112 in addition to the address

25   generating circuit 104. In such a case, the process

quantities need not to be transferred to the image

decoding section 112. It should be noted that the

17

control parameter is externally supplied and the data

quantity determining section 107 determines the

process quantity 105 every code block by using the

control parameter 101 in the above description.

5 However, the control parameter 107 may be all

contained in the coded image data CI. In this case,

the control data is read out from the coded image data

and the above process is carried out. Instead, a part

of the control parameter may be externally supplied

10 and the other may be contained in the coded image data

CI.

The image decoding section 112 is composed of

an arithmetic decoding section 116, a bit modeling

decoding section 118, an inverse quantization section

15 120 and an inverse wavelet conversion section 124.

The arithmetic decoding section 116 carries out an

arithmetic decoding process to the data stream 108

from the compressed data analyzing section 102 based

on the process quantity for the arithmetic decoding

20 process. The bit modeling decoding section 118

carries out a bit modeling decoding process to the

decoded data (context) obtained as a result of the

decoding process by the arithmetic decoding section

116 in the form of the bit plane every color component

25 based on the process quantity for the bit modeling

decoding process. As shown in Fig. 16, in the bit

modeling decoding process, contexts of coefficient

bits are checked after a bit plane decomposition is carried out to each code block. Thus, each of the bit planes is decomposed into three coding paths (sub bit planes), which are ordered. This is called the

5   coefficient bit modeling. Each coding path is subjected to an arithmetic coding process. The inverse quantization section 120 carries out an inverse quantization process to a processing result by the bit modeling decoding section 118 based on the

10 process quantity for the inverse quantization process. The inverse wavelet conversion section 124 carries out an inverse wavelet conversion process to the image WIn of the n-th layer obtained as a result of the inverse quantization process based on the process quantity for

15 the inverse wavelet conversion process.

The image decoding apparatus of the present invention can be realized by a CPU, a memory, and other LSIs in hardware. Similarly, the image decoding apparatus of the present invention can be realized by

20 a program having an image decoding function in software. Fig. 2 is a functional block which is realized through their cooperation. It could be easily understood to a person in the art that the functional block can be realized by only the hardware,

25 only the software or those combinations.

Next, the operation of the data quantity determining section 107 in the image decoding

apparatus 100 according to the first embodiment of the
present invention will be described.

As shown in Fig. 6, first, a coded image data
CI is supplied and is stored in the code buffer 103.
5   The control parameter 101 is supplied to the data
quantity determining section 107 (Step S10). The
control parameter 101 contains a unit process time Ti
of one image $(=t_{total}/$the total number of frames), the
number of code blocks (SB), a code block size (CBS),
10 the number of bit planes BP(CBi) (CBi shows a code
block number (coordinate)), the number of quantization
steps qs(SBi) (SBi shows a sub band number
(coordinate)), and a weighting coefficient W(CBi) of
the code block CBi.

15   Subsequently, the data quantity determining
section 107 determines process quantities of the
arithmetic decoding section 116, bit modeling decoding
section 118, inverse quantization section 120 and
inverse wavelet conversion section 124 prior to the
20 decoding processing in the image decoding section 112.
For example, the data quantity determining section 107
calculates a process time for the arithmetic decoding
process by the arithmetic decoding section 116, a
process time for finally outputting quantized data in
25 the form of the bit plane every color component from
the data, which is obtained as a result of the
arithmetic decoding process, by the bit modeling

20

decoding section 118, a process time for inversely
quantization process by the inverse quantization
section 120 to the processing result in the bit
modeling decoding section 118 and a process time for
5   carrying out the inverse wavelet conversion operation
by the inverse wavelet conversion section 124 to the
image WIn of the n-th layer obtained as a result of
the inverse quantization process. More specifically,
a whole process time (t_{total}) and the unit process time
10 Ti for one frame image previously allocated to the
image decoding apparatus 100 according to the first
embodiment of the present invention are confirmed.
After that, first, a data quantity processable within
the unit process time Ti by the inverse quantization
15 section 120 is determined. Subsequently, a data
quantity processable within the unit process time Ti
by the inverse wavelet conversion process section 124
is determined. Lastly, a data quantity processable
within the unit process time Ti by the arithmetic
20 decoding section and a data quantity processable
within the unit process time Ti by the bit modeling
decoding section are determined.

That is, an inverse quantization process
resolution levels IQ_subband_level(SB, BP(Cbi),
25 qs(Sbi) is calculated (Step S11). Subsequently, an
inverse wavelet decoding process resolution level
IW_subband_level(SB) is calculated (Step S12). After

21

that, the number of the layers which can be processed within the unit process time Ti is determined from the inverse quantization process resolution level and the inverse wavelet decoding process resolution level.

5   Subsequently, the data quantity IAB_subband_proc(Max(Liq,Liw),CBS,BP(Cbi),W(Cbi)) for the arithmetic decoding process and bit modeling decoding process is calculated based on the determined number of layers (Step S13).

10   In this way, the process by the inverse quantization section and the process by the inverse wavelet conversion process section in which the data quantity is smaller are first estimated and then the arithmetic decoding process and the bit modeling

15 decoding process are estimated. After that, data of each of the code blocks for the determined number of layers is read from the code buffer 103 and is supplied to the image decoding section 112. The other code blocks of the image are discarded.

20   Within the calculated data quantity, the arithmetic decoding process is carried out by the arithmetic decoding section 116, and the bit modeling decoding process is carried out by the bit modeling decoding section 118. After that, the inverse

25 quantization process is carried to the data after the bit modeling decoding process out by the inverse quantization section 120 within the calculated data

22

quantity. At this stage, the same images WIn of n
layers as those obtained when the inverse wavelet
conversion processes is carried out to the original
image n times are obtained. Subsequently, the inverse
wavelet conversion process is carried out to these
images (n-1) times by the inverse wavelet conversion
section 124 within the calculated process time and the
image WI1 of the first layer is generated. Moreover,
the inverse wavelet conversion process is carried out
once more to this image. Thus, the decoded image DI
is obtained. It should be noted that the above
structure is shown in Fig. 4, including buffers.

As mentioned above, the arithmetic decoding
process, the bit modeling decoding process, the
inverse quantization process and the inverse wavelet
decoding process are carried out to the coded image.
However, the data quantities of the above-mentioned
processes to the one frame image are different.
Therefore, if the decoding process of all the code
blocks CB from 3LL to 1LL is carried out when the
coded image CI is the image of the third layer, a
leaning is caused among the process times and it is
not efficient. When a plurality of continuous images
are decoded, it is efficient to carry out pipeline
processing. However, the pipeline processing cannot
be carried out if there is any leaning in the process
time.

For the above reasons, as shown in Fig. 1, the pipeline processing has been conventionally carried out in units of images and a process which cannot be ended within the unit process time is

5 ignored. Therefore, depending on the image, there is a case that the processes from the arithmetic decoding process to the inverse wavelet decoding process are fully carried out, but there is a case that the arithmetic decoding process to the inverse

10 quantization process are fully carried out but the inverse wavelet decoding process is stopped on the way because of the limitation of the process time. Thus, a deviation occurs between the data quality of the decoded image.

15 In the present invention, the decoding processes are divided into three process groups, i.e. a group of the inverse quantization process, a group of the inverse wavelet decoding process and a group of the process of the arithmetic decoding process and the

20 bit modeling decoding process. Fig. 5 schematically shows each process by taking the horizontal axis as the time axis. Referring to Fig. 5, when a predetermined time is allocated, the unit process time Ti which can be allocated to one frame image is

25 determined based on the number of frame images and the predetermined time. Thus, the process time which is allocated to each of the above three processes is

estimated and predetermined. For this reason, as
shown in Fig. 5, each process can be carried out in a
pipeline from the MSB side of the bit plane layers
within the process time previously allocated to the
5   process. Thus, each process group is carried out
primarily from the bit plane which has large influence
in perception so that the quality of the obtained
image becomes stable.

A procedure of the estimation of the number
10   of bit plane layers to be processed at the steps S11
and S12 is shown in Fig. 7A. Now, it is supposed that
the coded image CI is the 3-layer image. At the step
S11 of Fig. 6, the process time of the inverse
quantization process to the coded image is estimated.
15   As shown in Fig. 7A, the inverse quantization process
of the code books from 3LL to 1HH can be completed
within the unit process time Ti. Subsequently, the
process time of the inverse wavelet decoding process
to the coded image is estimated at the step S12. As
20   shown in Fig. 7A, only the code books from 3LL to 1LH
are ended within the unit process time Ti in the
inverse wavelet decoding process. Because the slower
one of the processes of the steps S11 and S12
determines the whole throughput, it is estimated that
25   the decoding process of 2 layers is possible as the
whole of system. That is, it is estimated that the
code books from 3LL to 3HH and from 2LL to 2HH can be

decoded within the unit process time Ti.

Next, the details of estimation of the process (Step S11) to determine the resolution level IQ_subband_level() in the inverse quantization process will be described, with reference to Figs. 10A and 10B. First, the process time t_{Q3LL} of the inverse quantization process to the code block CB 3LL by the inverse quantization section 120 is set to a summation time t ($t = t_{Q3LL}$ ($= t_0$)) at a step S71. Also, a level counter level_counter indicating the number of layers is set to "0". The process time t_{Q3LL} can be calculated based on algorithm and the size of the code block 3LL which is equivalent to the number of pixels. At a step S72, whether or not the summation time t is within the unit process time Ti is determined. Because the summation time t is within the unit process time Ti at this time, a step S73 is carried out next. Because the level counter is "0" at the step S73, the summation time t is changed to t = $t_{Q3LL}+3*4^0*t_{Q3LL}$. As a result, the summation time t becomes $4*t_{Q3LL}$ ($= t_1$). That is, the summation time t of the code blocks 3LL to 3HH in the third layer is estimated. Subsequently, the level counter is incremented by one at a step S74. Thus, the process time of the following layer becomes possible to be calculated. After that, the flow returns to the step S72.

The step S72 is carried out as above-mentioned, and then the step S73 is executed. At the step S73, the summation time t is changed to $t_1 + 3*4^1*t_{Q3LL}$. That is, the summation time is t (= t2) = $4*t_{Q3LL} + 3*4^1*t_{Q3LL} = 16*t_{Q3LL}$. As a result, the summation time t to the second layer is found.

When the above-mentioned process is repeated and the summation time t passes the unit process time Ti at the step S72, the step S75 is carried out and the resolution level Liq of the inverse quantization process is determined. The summation time t of the above-mentioned process, the value of the level counter, and the resolution level Liq are shown in Fig. 10B.

Next, the details of estimation of the process (Step S12) to determine the resolution level Liw (=IQ_subband_level()) of the inverse wavelet decoding process will be described, with reference to Figs. 11A and 11B. As seen from the comparison with Fig. 10A, the process shown in Fig. 11A is completely the same as while the inverse wavelet decoding process is adopted instead of the inverse quantization process.

First, the process time t_{Q3LL} of the inverse wavelet decoding process to the code block CB of 3LL by the inverse wavelet decoding section 124 is set on a summation time t (=t_{Q3LL} (=t_0)) at a step S81. The

27

level counter level_counter showing the number of
layers is set to "0". The process time
t_{Q3LL} can be calculated based on the algorithm and the
size of the code block 3LL which is equivalent to the
5 number of pixels, like the inverse quantization
process. At a step S82, whether or not the summation
time t is within the unit process time Ti is
determined. At this time, because the summation time
t is within the unit process time Ti, a step S83 is
10 carried out next. Because the level counter is "0" at
the step S83, the summation time t is calculated as t
= $t_{Q3LL}+3*4^0*t_{Q3LL}$. As a result, the summation time t
becomes $4*t_{Q3LL}$ ($=t_1$). That is, the summation time t
for one layer of the code blocks 3LL to 3HH is
15 estimated. Subsequently, the level counter is
incremented by one at a step S74. Thus, the process
time of the following layer is made possible to be
calculated. After that, the flow returns to the step
S82.

20   The step S82 is carried out, as mentioned
above, and then the step S83 is carried out. The step
S83 is carried out to set the summation time t to
$t_1+3*4^1*t_{Q3LL}$. That is, the summation time is set to t (=
t2) $= 4*t_{Q3LL}+3*4^1*t_{Q3LL} = 16*t_{Q3LL}$. As a result, the
25 summation time to the second layer is found.

         When the above-mentioned process is repeated
and the summation time t passes the unit process time

28

Ti at the step S82, the step S85 is carried out and the resolution level Liw of the inverse wavelet decoding process is determined. The summation time t of the above-mentioned process, the value of the level counter, and the resolution level Liw are shown in Fig. 11B.

Next, the details of estimation of the process at the step S13 will be described with reference to Fig. 8. Fig. 8 shows weight coefficients W(CBi) previously allocated to the code blocks CB from 3LL to 1HH for the process time calculation. The largest weighting coefficient "8" is set to the code block 3LL which has the code data of the lowest frequency component used to replay the most basic nature of the original image. Next, the weighting coefficient "4" is allocated to the code blocks 3HL and 3LH which are next important, and the weighting coefficient "2" is allocated to the code blocks 3HH, 2HL, 2LH and 2HH, which are next important. Last, the smallest weighting coefficient "1" is set to code blocks 1LL, 1HL, and 1LH which have the code data of the higher frequency components. The decoding process time of each code block is determined based on a corresponding weight coefficient and is reserved such that the arithmetic decoding process and the bit modeling decoding process of the code blocks CB from 3LL to 2HH can be ended within the unit process time

29

Ti. This result is shown in Fig. 7B. In other words, Fig. 7B is a diagram showing how to allocate the process time for the arithmetic decoding process and the bit modeling decoding process to each block. As described above, it is already determined that it is possible to decode the code books for two layers from 3LL to 3HH and from 2LL to 2HH and within the unit process time Ti. The process time is allocated to each code blocks in such a manner that a rate of the process time of each code block to the total process time is same as the rate of the weighting coefficient of the code block to a summation of the weighting coefficients of the code blocks 3LL to 2HH. Because the summation of the weighting coefficients of the code blocks 3LL to 2HH is "24", the process time $t_{cb}(3LL)$ allocated to the code block 3LL is $Ti*(8/24)$. In the same way, the process time $t_{cb}(2HH)$ allocated to the code block 2HH is $Ti*(2/24)$.

Next, the allocation of the process time to each code block in the arithmetic decoding process and the bit modeling decoding process will be described, with reference to Fig. 9 and Figs. 12 to 15. Fig. 9 shows a state that the bit planes to be processed within the process time allocated to each code block and shown in Fig. 7B are determined. As shown in Fig. 9, the process time which is longer than the other blocks is allocated to the code block 3LL. However,

all the bit planes cannot be decoded within the allocated process time. At this time, a part of the bit planes on the LSB side is discarded without being decoded. In this case, however, the bit plane on the MSB side shows the outline of the image and the bit plane on the LSB side shows a detail change in the image expressed in the bit plane form. For this reason, any influence in perception are not given often even if the bit planes on the LSB side are discarded without being decoded. Also, in the same way, there is a case where the allocated process times of the code blocks 3LL and 3LH are short so that the decoding process is not carried out until the last plane. On the contrary, there is a case that the process time is left, like the code block 3HL. In such a case, this left process time is first allocated to the decoding process of the code block 3LL, so that the decoding process of the bit planes of lower levels on the LSB side are decoded in the code block 3LL, resulting in finer decoded image. When the process time is still left even if the all the bit planes are processed, the left process time is allocated to another code block.

        Next, the estimation of process times of the arithmetic decoding process and the bit modeling decoding process will be described in detail. Referring to Fig. 12, a total of the weight

coefficients allocated to the code blocks of the two layers which have been determined to be processable is calculated at a step S91. The process time allocated to each code block CB is calculated at a step S92.
5 The process time for each code block is outputted at a step S93.

Next, the details of the steps shown in Fig. 12 will be described.

Referring to Fig. 13, first, the process of
10 calculating the total of the weight coefficients will be described. At a step S101, a variable i and s total weight W_{total} are set to "0". Whether or not the code block as an object belongs to the layers that should be processed is determined at a step S102.
15 When the code block object belongs to the layers, a step S103 is carried out and the weight coefficient allocated to the code block is added to the total weight W_{total}. Subsequently, a step S104 is carried out to increment the variables i by one and then the flow
20 returns to the step S102. In this way, the weight coefficients allocated to all the code blocks which belong to the layer which should be processed are added.

Next, the details of the calculation of the
25 process time (Step S92) will be described with reference to Fig. 14. At a step S111, a variable j is set to "0". Whether or not the code block object

32

belongs to the layers that should be processed is
determined at a step S112. When the code block object
belongs to the layers, a step S113 is carried out. In
this case, a summation time t allocated to the code
block is calculated based on (the weight coefficient
of the code block) / (total weight) * (unit process
time) (= $W(CB_j)/W_{total}*T_i$). Also, by dividing the
summation time t by a unit calculation time t_{cp} for the
coding path, the number of coding paths $CP(CB_j)$
possible to process in the code block is calculated.
After that, at the step S114, whether or not the
number of coding paths $CP_{ini}(CBj)$ initially allocated
to the code block is more than the calculated number
of coding paths $CP(CBj)$ is determined. If Yes, a step
S116 is carried out, and if No, a step S117 is carried
out. When the number of coding paths $CP_{ini}(CBj)$
initially allocated to the code block is more than the
calculated number of coding paths $CP(CBj)$, a remaining
process time is present in the process time. On the
contrary, when the number of coding paths $CP_{ini}(CBj)$
initially allocated to the code block is not more than
the calculated number of coding paths $CP(CBj)$, the
remaining process time is not present in the process
time.

At the step S116, the coding path is searched
sequentially from the code block 3LL among the already
processed code blocks which had been omitted because

33

the process time is lack and an addition process of the searched coding path for the remaining process time is carried out to the coding path. After that, the step S117 is carried out.

5   At the step S117, the number of bit planes is calculated by subtracting 1 from the calculated number of coding paths CP(CBj) possible to process or the number of coding paths CP(CBj) additionally processed and then by dividing the subtracting result by 3
10 corresponding to RGB. After that, the variable j is incremented by one at a step S118 and the tep S112 is again carried out for the following code block. It should be noted that the state of the above-mentioned process is shown in Fig. 9, if the data quantity
15 possible to process is read as the number of coding paths possible to process.

          Next, the details of the output processing of the data (step S93) will be described with reference to Fig. 15. At a step S121, a variable k is set to
20 "0". At a step S122, whether or not the code block as an object belongs to the layers to be processed is determined. If Yes, a step S123 is carried out. At the step S123, code data for the number of bit planes determined at the above step are outputted. After
25 that, the variable k is incremented by one at a step S124, and the step S122 is again carried out for the following code block.

In this way, in the present invention, the process time of each decoding process is previously estimated and the layers and code blocks to be processed are same over the decoding processes.

5   Therefore, the quality of the image after the decoding process is stable.

As described above, the address generating circuit 104 designates an address of coded data which should be transferred from the code buffer 103 to the

10   image decoding section 112, based on the output data from the data quantity determining section 107. However, the data quantity determining section 107 may output the process time or data quantity to each section of the image decoding section 112. Each

15   section may carry out the decoding process.

Also, in the above description, the weighting coefficients are fixedly allocated to the code blocks and stored in the data quantity determining section 107. However, the weighting coefficients may be

20   supplied from the outside to the data quantity determining section 107 and may be dynamically changed for every frame image.

In the above description, the unit process time is predetermined. However, the total process

25   time and the number of frame images may be supplied in the control parameter 101. In this case, the unit process time can be calculated from the total process

time and the number of frame images.

As described above, the present invention is described, by taking JPEG (Joint Photographic Expert Group) as an example, but the present invention is
5 applicable to another coding compression technique such as MPEG (Motion Picture Expert Group).